




12X b2

**DATE 28 SEP 2022** 



DETAIL


e2 •<u>e1</u>

e3-











SIDE VIEW

- DIMENSIONING AND TOLERANCING PER. ASME Y14.5M, 2009.
- CONTROLLING DIMENSION: MILLIMETERS
  DIMENSIONS D & E DO NOT INCLUDE MOLD
  PROTRUSIONS
- DIMENSIONS 6,61,62 DO NOT INCLUDE DAMBAR REMAIN. MARKING AREA.
- E4 IS FROM INNER LEAD TIP TO INNER LEAD TIP DISTANCE.





A

	MILLIMETERS			
DIM	MIN.	N□M.	MAX.	
Α	4.65	4.70	4.75	
A1	10.75	11.05	11.35	
A2	3.20	3.40	3.60	
АЗ	1.60	1.95	2.30	
Α4	5.70	6.00	6.30	
b	16.90	17.00	17.10	
b1	15.20	15.30	15.40	
b2	0.90	1.00	1.10	
b3	0.50 REF			
C	0.70	0.80	0.90	
D	54.80	55.00	55,20	
D1	46.20	46.50	46.80	
D2	50.70	51.00	51.30	

	MILLIMETERS				
DIM	MIN.	N□M.	MAX.		
E	54.80	55.00	55.20		
E1	40.50	40.80	41.10		
E2	29.80	30.10	30.40		
E3	49.40	49.60	49.80		
E4	61.75	62.00	62.25		
е	10.30 BSC				
e1	11.45 BSC				
e2	2.40 BSC				
e3	4.20 BSC				
е4	4.50 BSC				
F	6.45	6.50	6,55		
L	19.60	20.00	20.40		
L1	3.10	3.50	3.90		
L2	5.70	6.00	6.30		
L3	9.70	10.00	10.30		
М	10° REF				

## **GENERIC MARKING DIAGRAM\***

20 COD ZZZ **ATYWW** 

XXXXXXX NNNNNNN ZZZ = Assembly Lot Code

= Assembly & Test Site Code ΑT

= Year

WW = Work Week

XXXX = Specific Device Code

NNN = Serial Number

\*This information is generic. Please refer to device data sheet for actual part marking. Pb-Free indicator, "G" or microdot "=", may or may not be present. Some products may not follow the Generic Marking.

DOCUMENT NUMBER:	98AON86580G	Electronic versions are uncontrolled except when accessed directly from the Document Repository. Printed versions are uncontrolled except when stamped "CONTROLLED COPY" in red.		
DESCRIPTION:	AHPM15-CEA		PAGE 1 OF 1	

onsemi and ONSEMI are trademarks of Semiconductor Components Industries, LLC dba onsemi or its subsidiaries in the United States and/or other countries. onsemi reserves the right to make changes without further notice to any products herein. onsemi makes no warranty, representation or guarantee regarding the suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. **onsemi** does not convey any license under its patent rights nor the rights of others.